#### antes de utilizar este guia...

Verifique se você fez o seguinte:

- instalou o software da hp deskjet série 995c
- configurou a impressora
- instalou um cartão PC 3Com Bluetooth no seu laptop



#### abra o Gerenciador de conexão 3Com Bluetooth

1. Clique em Iniciar > Programas > 3Com Mobile > Gerenciador de conexão Bluetooth.

O Gerenciador de conexão Bluetooth é aberto.





#### abra a caixa Portas COM Bluetooth

🐗 🕹 😌   🐚 🖻	) 🤗 🗝 🕤 📍	Ge SCON
S		
~		
hp deskjet 995c S/N		
hp deskjet 995c S/N US13S3K01YAP		
hp deskjet 995c S/N US13S3K01YAP		
hp deskjet 995c S/N US1353K01YAP		
hp deskjet 995c S/N US13S3K01YAP		

#### 2. Clique em Ferramentas > Porta Com.

A caixa de diálogo Portas COM Bluetooth é aberta.



Etapa 2 de 9

#### observe a porta COM Bluetooth

Port:	3Com Bluetooth Serial	Host (CDM5)		
Profile:	Serial Port			
Client Ports				
Port		Profile	Remote Device	Edit
3Com Blue	tooth Serial Client (CDM4)	Serial Port	00.00.00.00.98)	
3Com Blue	tooth DUN Client (COM6)	Dial-up Networking	Prompt	
3Com Blue	tooth Fax Client (CDM7)	Fax	Prompt	
Scow Bine	COULD THIN CREAT (COWA)	LMN MODESS	riompi	

**3.** Observe a porta COM do cliente serial 3COM Bluetooth.

Neste exemplo, a porta COM é COM4





#### abra a pasta Impressoras

4. Clique em Iniciar > Configurações > Impressoras.

A pasta Impressoras é aberta.





# abra a caixa de diálogo Propriedades da impressora



 5. Na caixa de diálogo Impressoras, clique no ícone da impressora hp deskjet 995c e clique em Arquivo > Propriedades para exibir a caixa de diálogo Propriedades da impressora.

Etapa 5 de 9



#### clique na guia Portas

Color Management	Security About
Dordeskjet 995c. sere	
Location:	
Comment:	
Model: hp deskjet 995c serier	:
Features	
Color: Yes	Paper available:
Double-sided: Yes	
Staple: Unknown	
Speed: Unknown	
Maximum resolution: Unknown	<u> </u>
Disting	Preferences Print Test Page
Panary	

**6.**Clique na guia **Portas** na caixa de diálogo Propriedades da impressora.

Etapa 6 de 9



#### selecione a porta Bluetooth

General         Shang         Pots         Advanced           We devise SMS tasks:         The devise SMS tasks:         The devise SMS tasks:         The devise SMS tasks:           Marcel Addition         December 3 will part to the tast test head point.         The devise SMS tasks:         The devise SMS tasks:           Marcel Addition         December 3 will part to the tast test head point.         December 3 will part to the tast test head point.           Direct Scale Float         December 3 will part to the tast test head point.         December 3 will part to the tast test head point.           Direct Scale Float         December 3 will part to the tast test head point.         December 3 will part to the tast test head point.           Direct Scale Float         December 3 will part to the tast test head point.         December 3 will part to the tast test head point.           Direct Scale Float         December 3 will part to the tast test head point.         December 3 will part to the tast test head point.           Direct Scale Float         December 3 will part to the tast test head point to the tast test head point.         December 3 will part to the tast test head point test head point to tast test head point test head p	Color M	lanagement	Security	About
by by by degree VBCs unere bits to be (clowing port(s), Documents with piret to the Inst tee bendered and: UP12 Prover Part UP13 Prover Part UP13 Prover Part UP13 Prover Part UP13 Prover Part Dest Dest Part Dest Dest Part Dest Part Inst Part Inst Part Dest Part Inst Part Inst Part Inst Part Dest Part Inst Pa	General	Sharing	Ports	Advanced
Pro Market uncol Lesses     Proceedings on the International System Conference Onter Con	Ale .	1.11.005		
her to the (dowing port(s) Documents will part to the fast test here to the documents only part to the fast test Prot Description Preter Prot Description Preter Proto Preter 2004 Sear Part 2004 Sear P	۹۳ 💞	aeskiet 3300 sene	5	
Are the 6 downg port(3). Downersk with part to the first lites     hand book downg port(3). Downersk with part to the first lites     hand to book down and the first lites     part of the first lites and the first lites a				
Marke Julia Port Decopton Peter □ PT2 There Peter □ PT2 There Peter □ DT2 Sever Peter □ DT2 Sever □ DT2 Sever Peter □ DT2 Sever Peter □	Print to the fi	ollowing port(s). Do	cuments will print to th	e first free
Total CP         Description         If Weter         P           Total CP         Description         If Weter         P           DVD1         Description         If Weter         If Weter         P           DVD1         Description         If Weter         If Weter         If Weter         If Weter           DVD2         Description         If Weter	uneckeu por		(=	
DFT Dever Pro     DFT Dev	Port	Description	Panter	-
Contact Search Part     C		Panter Port		
CON2 See For     CON3 See For     C		Printer Port		
DOND, See Prov     PLE: Plant to File     Add Port Delete Port     Configure Port      Findle bidirectional support     Enable printer pooling		Senal Port		
ERLEG From Earling         No         PLE         Point of Plan         No         Point of Plan         Debits Point         Configure Point.         Configure Point.         Enable Spiriture Gooding           Enable Spiriture gooding         Enable Spiriture gooding         Enable Spiriture gooding         Enable Spiriture gooding		Serial Port		
PLE: Pint to File     Add Port     Delite Port     Configue Port      Endele bidrectional support     Endele pinter pooling	2 00M4	Serial Port	N	
Add Port Delete Port Configure Port Configure Port Enable binkerctional support Enable printer pooling	FILE:	Print to File	4	-
Add Port Delete Port Conligue Port 7 Enable bidirectional support 6 Enable printer pooling	·	C.	0	
Enable bidirectional support     Enable printer pooling	Add P	ort	Delete Port	Configure Port
Enable printer pooling	. Cashie k	denotion of summer t		
Enade print pound	Cashle o	interneting support		
	Enable p	inter pooring		
		-		

**7.** Selecione a porta COM sem fio Bluetooth, observada na etapa 3.

Neste exemplo, a porta COM sem fio Bluetooth é COM4. A porta pode ser diferente no seu computador.

Certifique-se de selecionar a porta COM observada na etapa 3.

Etapa 7 de 9



#### feche a caixa de diálogo Propriedades

**8.** Clique em **Aplicar** e em **OK** para fechar a caixa de diálogo Propriedades da impressora.





#### parabéns - instalação concluída

**9.** Teste o recurso de impressão sem fio Bluetooth, imprimindo um documento pequeno.

Para obter instruções sobre impressão, vá para o site de impressão sem fio Bluetooth da HP e faça o download do documento *Impressão sem fio Bluetooth: impressora hp deskjet série 995c*.

Retornar para o site de impressão sem fio Bluetooth da HP

Etapa 9 de 9