

# Technical Specifications

Model t278d	DK399A
<b>Processor &amp; Speed</b>	2.6HT GHz/800 Intel® Pentium® 4 Processor – PGA478
<b>Chipset</b>	Intel® 865G
<b>Motherboard</b>	P4SD-LA-GL6E
<b>RAM</b>	256/2700 MB DDR SDRAM
Maximum	4 GB (4x1024MB DDR SDRAM)
Sockets	Four 184-pin DDR DIMMs
Size	128, 256, 512 and 1024 MB DDR DIMMs
<b>Free DIMM Sockets</b>	Three
Pairs Required	No
Type Supported	JEDEC unbuffered DDR SDRAM DIMM specification
<b>Cache</b>	8KB Data Cache + Trace Cache L1, 1 MB L2 Integrated on Processor module
<b>Hard Drive</b>	80 GB (7200 RPM)
<b>Optical Drive</b>	DVD+R/RW Drive
Transfer rates	Write: Up to 10x (CD-RW) Write: Up to 16x (CD-R) Write: Up to 4x (DVD+RW) Read: Up to 40x (CD-RW) Read: Up to 40x (CD-R/CD-ROM) Read: Up to 8x (DVD+RW)
<b>Diskette Drive</b>	None
<b>6 in 1 Card Reader</b>	Compact Flash I/II; Memory Stick; MMC/SD; Smart Media
<b>Fax/Data Modem</b>	V.92 56Kbps
Fax Speed	Up to 14.4Kbps
Data Compression	V.42 bis
Error Correction	V.42
EIA Fax Commands	Class 1
<b>Video Graphics</b>	AGP 8X Graphics Card
Controller	nVidia GeForce4™ MX-440
Video Memory	64 MB DDR, not upgradeable
Video Connectors	Composite & S-Video – PAL or NTSC
<b>Network Card</b>	10/100 BaseT, Integrated
<b>1394 Card</b>	IEEE-1394, Integrated
<b>MPEG-1/2</b>	MPEG-2 for full-screen, full-motion digital video
<b>TV Tuner</b>	TV Tuner Card
<b>Sound</b>	AC'97, 6 Channel, Integrated on MB
Controller	Realtek ALC650
<b>Chassis</b>	Jaguar, 250HV PSU
<b>USB Interface Specification</b>	USB 2.0
<b>External Ports</b>	6= USB, 1= serial, 1= parallel, 2=1394
Front I/O Connector	2= USB, 1= 1394; 6 in 1 Card Reader; 1= Microphone; 1= Line In; 1= Headphone
<b>Expansion Slots (Total)</b>	3= PCI, 1= AGP
<b>Expansion Slots (FREE)</b>	1= PCI
<b>Drive Bays (Total)</b>	Two 5.25" external, One 3.5" external, Two 3.5" internal
<b>Drive Bays (FREE)</b>	One 5.25" external, One 3.5" internal
<b>Keyboard/Mouse</b>	One-touch Enhanced Keyboard, PS/2 Optical scrolling mouse

Copyright Hewlett-Packard Co. 1994-2003

This information is subject to change without notice and is provided "as is" with no warranty.

Hewlett-Packard shall not be liable for any direct, indirect, special, incidental or consequential damages in connection with the use of this material.