

Hewlett-Packard Certificate of Volatility

Model: HP LaserJet Managed Flow MFP E725XXz	Part Number: Managed X3A59A= E72525z X3A62A= E72530z X3A65A= E72535z	Address: Hewlett Packard Company 11311 Chinden Blvd Boise, ID 83714
--	--	---

Volatile Memory

Does the device contain volatile memory (Memory whose contents are lost when power is removed)?

Yes No If Yes please describe the type, size, function, and steps to clear the memory below

Type (SRAM, DRAM, etc.):	Size:	User Modifiable:	Function: Operation system and print/scan buffer	Steps to clear memory: When the printer is powered off the memory is erased.
DDR3 - DRAM	HP Formatter 3GB- Obsidian 1 GB -Accel board 4 GB - Main Formatter	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No		
Type (SRAM, DRAM, etc.):	Size:	User Modifiable:	Function:	Steps to clear memory:
		<input type="checkbox"/> Yes <input type="checkbox"/> No		

Non-Volatile Memory

Does the device contain non-volatile memory (Memory whose contents are retained when power is removed)?

Yes No If Yes please describe the type, size, function, and steps to clear the memory below

Type (Flash, EEPROM, etc.):	Size:	User Modifiable:	Function:	Steps to clear memory:
IOD EEPROM	32KB	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No	Store customer setting data for backup/restore	There are no steps to clear this data.
Type (Flash, EEPROM, etc.):	Size:	User Modifiable:	Function:	Steps to clear memory:
HP side: SPI Flash	4MB	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	Contains the boot code and factory product configuration data required for the device to function. User modifications are limited to downloading digitally signed HP firmware images.	There are no steps to clear this data
Type (Flash, EEPROM, etc.):	Size:	User Modifiable:	Function:	Steps to clear memory:
Samsung MSOK : MSOK – TPM NVRAM MSOK - EEPROM MSOK – CRUM	2 KB 32 KB 32 KB	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No	TPM NVRAM - stores HP-signed immutable ID certificate and associated RSA key pair in locked memory. EEPROM - stores device lifecycle data (e.g. device page counts), copy of device speed license, and SED (self-encrypting drive) drive lock password. CRUM - stores device page counts, consumables information, device speed	Drive lock password can be changed through the device embedded web server interface. No other data stored on the MSOK can be cleared.

		information, and product serial number.	
--	--	---	--

Mass Storage

Does the device contain mass storage memory (Hard Disk Drive, Tape Backup)? <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No If Yes please describe the type, size, function, and steps to clear the memory below				
Type (HDD, Tape, etc.): 2 – Hard Drives (1 – HP formatter & 1 – Main board)	Size: 320GB/ea	User Modifiable: <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	Function: Stores customer data, OS, applications, digitally signed firmware images, persistent data, and temporary data used for processing and system functions.	Steps to clear memory: 1. Secure Storage Erase – Areas temporary files and job data by overwriting information overwriting information one or three times. 2. Secure Disk Erase – Erases files when jobs finish processing by overwriting them one or three times. 3. Secure File Erase – Erases files when jobs finish processing by overwriting them one or three times.

Optional Mass Storage

Does the device contain mass storage memory (Hard Disk Drive, Tape Backup)? <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No If Yes please describe the type, size, function, and steps to clear the memory below				
Type (HDD, Tape, etc.): Optional Formatter HDD 500 GB FIPS Encrypted HDD	Size: 500GB	User Modifiable: <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No	Function: Stores customer data, OS, applications, digitally signed firmware images, persistent data, and temporary data used for processing and system functions.	Steps to clear memory: 1. Erase and Unlock Encrypted Disk – This changes the Encryption keys rendering all data unreadable. 2. Secure Storage Erase – Areas temporary files and job data by overwriting information overwriting information one or three times. 3. Secure Disk Erase – Erases files when jobs finish processing by overwriting them one or three times. 4. Secure File Erase – Erases files when jobs finish processing by overwriting them one or three times.

USB

Does the item accept USB input and if so, for what purpose (i.e Print Jobs, device firmware updates, scan upload)? <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No If Yes please describe below	
Print jobs, HP digitally signed firmware upgrades, 3rd party application loading. USB ports can be disabled.	
Can any data other than scan upload be sent to the USB device)? <input checked="" type="checkbox"/> Yes <input type="checkbox"/> No If Yes please describe below	
Diagnostic service logs can be uploaded. Print files can be printed via a USB thumb drive.	

RF/RFID

Does the item use RF or RFID for receive or transmit of any data including remote diagnostics. (e.g. Cellular phone, Bluetooth) <input type="checkbox"/> Yes <input checked="" type="checkbox"/> No If Yes please describe below	
Purpose:	
Frequency:	Bandwidth:
Modulation:	Effective Radiate Power (ERP):
Specifications:	

Other Transmission Capabilities

Does the device employ any other methods of non-wired access to transmit or receive any data whatsoever (e.g. anything other than standard hard wired TCP/IP, direct USB, or parallel connections)? Yes No If Yes please describe below:

Purpose: WiFi Direct Print

Frequency: 2.4 GHz, 5GHz

Bandwidth: 2401 - 2495 MHz; depending on selected channel in 2.4GHz band.
5180 - 5825 MHz; depending on selected channel in 5GHz band.

Modulation:

Effective Radiate Power (ERP):

Specifications: 802.11 b/g/n

Other Transmission Capabilities

Does the device employ any other methods of non-wired access to transmit or receive any data whatsoever (e.g. anything other than standard hard wired TCP/IP, direct USB, or parallel connections)? Yes No If Yes please describe below:

Purpose: Device Beaconsing, Secure Print Apps

Frequency: 2.4 GHz

Bandwidth: 2400-2483.5 MHz; depending on selected channel.

Modulation:

Effective Radiate Power (ERP):

Specifications: BTLE4.0 compliant

Other Capabilities

Does the device employ any other method of communications such as a Modem to transmit or receive any data whatsoever? Yes No If Yes please describe below:

Purpose:

Specifications:

Author Information

Name	Title	Email	Business Unit
John Mast	Technical Marketing Engineer	Technical.Marketing@hp.com	IPG
Robert Mejia	System Engineer	Technical.Marketing@hp.com	IPG

Date Prepared: 9/14/2018